


BTI 2 Refilling Instructions



BTI 2 Refilling Instructions



Chemteq, Inc.
600 West 24th Street, Suite B
Norfolk, Virginia 23517
USA

<http://www.chemteq.net>
Tel: 757-622-2223 / Toll free: 855-CHEMTEQ

NOTICES

These instructions are prepared exclusively for the owner of Chemteq Breakthrough Indicators 2 (BTI 2). The content of these instructions are proprietary information and are to be used only to understand, refill and maintain the BTI 2. By receiving this document, the recipient agrees that neither this document nor the information disclosed within nor any part hereof shall be reproduced or transferred, physically, electronically or in any other form, or used or disclosed to others for manufacturing or for any other purpose except as specifically authorized in writing by Chemteq, Inc.

© 2009 Chemteq, Inc. All Rights Reserved. No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language in any form by any means without the prior written permission of Chemteq, Inc.

The information in this document is subject to change without notice. The images and drawings used in these instructions are for explanatory purposes only and may not be identical with the actual device in their appearance, size, color or positions.

Chemteq is registered trademark of Chemteq, Inc.

Breakthrough Indicators are manufactured by Chemteq, Patent Pending.

Made in the United States of America



READ AND UNDERSTAND ALL INSTRUCTIONS BEFORE USE

These Instructions must be read and understood by user before operating this product or using its accessories, in order to ensure proper and safe use of this product.

Read and understand all applicable federal, state, and local environmental health and safety laws and regulations, including OSHA. Ensure complete compliance with all applicable laws and regulations before and during use of this product.

Do not substitute, modify, or omit parts or components. Use exact manufactured replacement parts in configurations specified by the original manufacturer.

Contact Chemteq’s Service Department for any questions regarding these instructions or to arrange for a Returned Material Authorization (RMA).

Table of Content

1. Instructions.....	3
1.1. Remove bottom porous plug using miniature-hook pick (Figures 1 & 2)	3
1.2. Remove indicator retainer (Figure 3).....	3
1.3. Remove exhausted colorimetric indicator (Figures 4 & 5).....	3
1.4. Remove cotter pins using small pair of pliers and miniature-hook pick (Figure 6 & 7)	4
1.5. Carefully remove the top retainer (Figures 8 & 9).....	4
1.6. Empty consumed charcoal (Figure 10).....	4
1.7. Allow indicator body to stand for 24 hours or blow clean air through it to remove any traces of contaminants (Figure 11)	4
1.8. Inserts suitable colorimetric indicator assembly; see Table 2, (Figures 12 & 13).....	4
1.9. Replace bottom porous plug (Figures 14 & 15)	4
1.10. Replace red plug (Figure 16).....	5
1.11. Turn BTI 2 top side up and charge top with suitable activated charcoal (Figure 17).....	5
1.12. Replace top porous plug (Figure 18).....	5
1.13. Replace top retainer, insure to align the green mark on retainer and the indicator (Figure 19)	5
1.14. Insert the three cotter pins to hold top retainer to indicator body, use pliers to secure pins in place (Figures 20 & 21)	5

BTI 2 Refilling Instructions

1. Instructions



Table 1: Components of the BTI 2 Refill Kit

Item No.	Description	No. of Items	Part Number
1	Colorimetric indicator Assembly	1	See table 2 for specific indicator
2	Cotter Pin ($\frac{1}{16}'' \times \frac{1}{2}''$)	3	436-1300
3	Porous Plug	2	401-1400
4	Sorption media	1	Acids (PN: 401-5200), ammonia (PN: 403-5200), hydrogen sulfide (PN: 406-5200), formaldehyde (PN: 411-5200), hydrazine (PN: 408-5200)

Table 2: BTI 2 Colorimetric Indicator Assemblies

Item No.	Colorimetric indicator Assembly	No. of Items	Part Number
1	Acid Gases and Vapors	1	401-1600
2	Ammonia Vapor	1	403-1600
3	Ammonia & Hydrogen Sulfide	1	402-1600
4	Formaldehyde Vapor	1	411-1600
5	Hydrazine Vapor	1	408-1600
6	Hydrogen Sulfide Gas	1	406-1600

Table 3: Required Tools

Item No.	Tool	No. of Items	Part Number
1	Miniature-Hook Pick 	1	431-9100
2	Small Pair of pliers 	1	NA

1.1. Remove bottom porous plug using miniature-hook pick (Figures 1 & 2)



Figure 1




Figure 2

1.2. Remove indicator retainer (Figure 3)



Figure 3

1.3. Remove exhausted colorimetric indicator (Figures 4 & 5)




Figure 4




Figure 5

BTI 2 Refilling Instructions

1.4. Remove cotter pins using small pair of pliers and miniature-hook pick (Figure 6 & 7)




Figure 6




Figure 7

1.5. Carefully remove the top retainer and top porous plug (Figures 8 & 9)




Figure 8




Figure 9

1.6. Empty consumed sorption media (Figure 10)



Figure 10

1.7. Allow indicator body to stand for 24 hours or blow clean air through it to remove any traces of contaminants (Figure 11)



Figure 11

1.8. Inserts suitable colorimetric indicator assembly; see Table 2, (Figures 12 & 13).




Figure 12




Figure 13

1.9. Replace bottom porous plug (Figures 14 & 15)




Figure 14




Figure 15

BTI 2 Refilling Instructions

1.10. Replace red plug (Figure 16)



Figure 16

1.11. Turn BTI 2 top side up and charge top with suitable sorption media (Figure 17)



Figure 17

1.12. Replace top porous plug (Figure 18)



Figure 18

1.13. Replace top retainer, insure to align the green mark on retainer and the indicator (Figure 19)



Figure 19

1.14. Insert the three cotter pins to hold top retainer to indicator body, use pliers to secure pins in place (Figures 20 & 21)




Figure 20



Figure 21

**PLEASE CALL US AT 757-622-2223 OR EMAIL US AT info@chemteq.net
FOR ANY QUESTIONS REGARDING THESE INSTRUCTIONS**

BTI 2 Refilling Instructions



600 West 24th Street, Suite B, Norfolk, VA23517
Tel: 757-622-2223, Toll-free 855-243-6837 (855-CHEMTEQ)
Email: sales@chemteq.net
<http://www.chemteq.net>